

PRODUCT



SOLARWATT Battery vision

clusterbox 1.0

The Battery vision clusterbox enables the operation of multiple Battery vision storage units (each in combination with a SOLARWATT Inverter vision three) with only one main meter in the same energy system.

The clusterbox coordinates battery charging between the individual devices, receives control signals (e.g. from the grid operator) and distributes them to the individual inverterbattery-pairs.

ELECTRICAL CONNECTION

Power supply	10 - 27 V_{DC},via power supply unit (included) or communication bus to the inverter	
Power consumption	20-30 W	

DISPLAY AND CONTROL ELEMENTS

Start button	on / off
LEDs	RUN / COM / CLOUD

INPUTS AND OUTPUTS

Connection	Interface
RJ45	potential-free contacts, 6-24 V
RJ45	RS485
RJ45	3 x Relay inputs and outputs
RJ45	RS485
RJ45	Ethernet
RJ45	Ethernet
Antenna	
	RJ45 RJ45 RJ45 RJ45 RJ45 RJ45

Tested in accordance with EU and UK directives and regulations (CE/UKCA): 2014/35/EU (LVD) 2011/65/EU (RoHS) (voluntarily) 2014/30/ EU (EMC) 2014/53/EU (RED)

GENERAL DATA

	SOLARWATT Inverter vision three Chint Meter DTSU 666	
Supported devices	Note: Only one DTSU 666 is required for the entire system (included in the scope of delivery of the inverters).	
Installation	Wall mounting	
Storage Temperature	-40 °C to 70 °C	
Operation Temperature	-30 °C to 60 °C	
Relative Luftfeuchtigkeit	< 95 % (no condensation)	
Dimensions (WxHxD) Dimensions Packging	260 x 192 x 88 mm 350 x 280 x 165 mm	
Weight (netto / brutto)	2.3 kg / 3.5 kg	
IP rating	IP65 (Indoor and Outdoor)	
Protection class	I	
Overvoltage Category	II	



For information in accordance with the EU Data Act, scan the QR code or follow the link:

www.solarwatt.com/eu-data-act-en.

BENEFITS

- Connection of up to 10 Inverter vision three + Battery vision pairs in grid-connected operation
- Connection of up to 4 Inverter vision three + Battery vision pairs in emergency power mode
- · Wall-mounted metal housing in Solarwatt vision design

DIMENSIONS

